

Welcome!

MVOICE series speakerphone is specially designed to fulfill the customers' increasing demand for web-conferencing calls, hands-free calls and teleconferencing.

MVOICE 5000 USB speakerphone can connect to computer with USB cable to realize hands-free audio and video conference based on internet application.

Highlights and features

- Connect to PC via USB.
- Three built-in 360° coverage microphones.
- Hi-Fi sound quality.
- DSP noise and echo cancellation.
- Low power consumption.



5. Choose two microphones

- 6. Choose single microphone
- 7. Speaker
- 8. Microphones

Connecting to PC or laptop

Plug and play, simply connect the MVOICE 5000 to the USB port on your PC with USB cable. Support Windows XP, Windows Vista, Windows7/8/10 etc.

Attention: MVOICE 5000 works excellently in web-conferencing via Skype or other VoIP software. The PC can automatically identify the MOVICE device, but you may need to choose MEETEASY USB AUDIO in application software. For example, you would need to choose MEETEASY USB AUDIO in Skype audio setting section.

Mute the speaker

Press the button <a>v can mute the speaker, the button turns orange

Mute the microphones

Increase the volume

Press the button <a>+ can increase the volume level

Decrease the volume

Press the button **I** – can decrease the volume level

Separate microphone selection

In normal room conditions, the reception distance can reach to 3 meters. Built-in three microphones provides with 360-degree coverage.

For group meetings, all three microphones open can make proper audio reception of all participants.

In a conference room with weak sound absorption and strong acoustic reflection (particularly the glass rooms), and the talker is far from the microphones, the microphones will receive the echo from different directions, which is impossible to eliminate completely. The other side of the conference may hear unclear voice. Speak close to the microphone and use only one microphone pointed to the speaker can receive the voice more clearly.

Press $ensuremath{\Downarrow}$ button can turn on one microphone and mute two others in turn.

Press \bigcup button can turn on two microphones and mute the rest one in turn.

Specification:

System requirements	Windows XP/Windows Vista/Windows7/8/10 etc.
Connections	USB version 2.0
Max volume	83dB
Speaker frequency	30-16KHz
Microphone frequency	30-16KHz
Power voltage	5V DC
Power consumption	300mAh max.
Operating temperature	5°C-40°C
Storage temperature	-30℃-55℃
Accessories	6ft USB cable/User Guide/Protective bag/Gift box
Compliance	RoHS/FCC/CE

Meeteasy Technology Limited

Add:6F Jianda Building,Keyuan Road,Science and Technology Park,Nanshan District,Shenzhen,518053,China E-mail: info@meeteasy.com.hk

Tel:(+86) 755 8884 1683 Fax:(+86) 755 2690 5650

For more information, please visit

www.meeteasy.com.hk